



RATIO (Ip / Is, (A))	BURDEN (VA) CI 1	BURDEN (VA) CI 0.5	ODERING CODE
800/5	5.0	5.0	JP-812-0800
1000/5	7.5	5.0	JP-812-1000
1200/5	7.5	5.0	JP-812-1200
1500/5	10	7.5	JP-812-1500
1600/5	10	7.5	JP-812-1600
2000/5	10	10	JP-812-2000
2500/5	10	10	JP-812-2500
3000/5	15	10	JP-812-3000
3200/5	15	10	JP-812-3200
4000/5	20	15	JP-812-4000

Ratio: From 800/5A to 4000/5A

Designed by ILEC	Checked by	Approved by	Date	DD/MM/YYYY 12/03/2021
ILEC Electrical		JP-812 Current Transformer		
JP-812_1.1		Edition 1.1	Sheet 1 / 1	